

Zone control modules

Project Information

| | |
|---------------------------------|-----------------|
| Job name : | Location : |
| Engineer : | Date submitted: |
| Contractor : | Submitted by: |
| Manufacturer's representative : | Approved by : |

Technical data

Prop 65 label required? Yes

Product information and application use

The Uponor Zone Control Module is a printed circuit control and a diagnostic device used with Uponor thermostats, zone valves and two-wire or four-wire actuators. It is internally fused for protection from over-current or direct-shorts from the power-supply transformer. The module provides connection to the power supply transformer, the interconnections between the individual thermostats and their respective thermal actuators or zone valves, as well as the connection between end switches and respective pumps or boiler relays.



| Part name | Part no. | A [Inch] | B [Inch] | C [Inch] | Weight per UOM [lbs/UOM] |
|---|----------|----------|----------|----------|--------------------------|
| Replacement Fuse (2 amps), 4/pkg. | A3030009 | - | - | - | 0.05 |
| Replacement Fuse (4 amps), 4/pkg. | A3030010 | - | - | - | 0.05 |
| Three-zone Control Module for Two and Four-wire Operation | A3031003 | 6.408 | 2.8 | 1.099 | 0.45 |
| Four-zone Control Module for Two and Four-wire Operation | A3031004 | 8.408 | 2.8 | 1.099 | 0.5 |

Installation

Mount the control module in a convenient location above the actuators using double-sided foam tape or mounting holes with suitable hardware. To combine zones to a single thermostat, connect #3 terminals of the thermostat input blocks with a suitable jumper. Use a module jumper (provided) to connect modules together in a series. Refer to the Uponor Zone Control Module Instruction Sheet for additional information.

Related applications

- Radiant Heating and Cooling Systems
- Permafrost Protection Systems
- Turf Conditioning Systems

| Codes | Standards | Listings |
|-------|-----------|----------|
| - | - | - |

Notes

- 2 amp fuse for ZCM3/4 (A3031003/A3031004) for End Switch relay protection
- 4 amp fuse for ZCM3/4 (A3031003/A3031004) for main power protection
- Max. Uponor TAs (A3010522)/50VA Transformer: 12 (rating at 24VAC)
- Max. Uponor MVAs (A3020522)/50VA Transformer: 7 (rating at 24VAC)
- Max. Uponor TAs (A3030522)/50VA Transformer: 12 (rating at 24VAC)

Footnotes

Contact information

| | | |
|---|--|--|
| - | <p>Uponor Inc. 5925 148th Street West Apple Valley, MN 55124 T 800.321.4739 F 952.891.2008</p> | <p>Uponor Ltd. 6510 Kennedy Road Mississauga, ON L5T 2X4 T 888.594.7726 F 800.636.9517</p> |
|---|--|--|